

TerraTec Aureon 5.1 USB (MKII) under Windows Vista

A generic USB Audio driver will be installed automatically by Windows Vista if you plug the Aureon into a USB port of your PC. You can use the external Soundcard complete without limitation, except an AC3 signal over the S/PDIF Out. This function is not available at the moment.



Some configurations are necessary yet to use all connected Speaker. Open the control panel of your OS. You will find a submenu sound. Click on it.

layback	Recording	Sounds				
Select a	playback de	vice belo	ow to m	odify it	s settings:	
0	Lautsp High D Not pl	recher efinition ugged in	Audio	-Gerät		
	Digital High D Workin	es Ausga efinition ng	begerä Audio	it (SPDIF -Gerät	0	
	Lautsp USB Au	recher Idio Ig	(1)			
	SPDIF- USB Au Workin	S <mark>chnittst</mark> Idio Ig	elle			
(3	3)				(2)	
Config	gure			<u>S</u> et	Default	Propertie

Please mark the USB Audio Device (1) and click Set Default (2). Click the Configure button (3).



🅞 🛐 Speaker Setup	
Choose your configuration Select the speaker setup below that is most like the configuration on your computer. Audio channels:	
Stereo 5.1 Surround	SI CONTRACTOR
▶ <u>I</u> est	Click any speaker above to test it.
	Next Cancel

Please Choose 5.1 Surround and click Next.

🗿 📴 Speaker Setup	
Customize your configuration	
Check the boxes below to indicate which speakers are present in your surround configuration.	
Optional speakers: Image: Center Image: Subwoofer Image: Side pair Image: Rear pair	
	Click any speaker above to test it.
	Next Cancel

Here your have to select Center, Subwoofer and Side pair.

AUREON 5.1 USB MKII Short-Instruction for Windows Vista (Ver. 1)

🕒 🧃 Speaker Setup	
Select full-range speakers Satellite speakers usually have a limited dynamic range and require that they be used with a subwoofer. If your configuration includes full-range speakers, select them below. Full-range speakers:	
	Click any speaker above to test it.

Please checkmark the necessary options and click Next.

G	Speaker Setup	
	Configuration complete	
	If you click "Finish" your new settings will be applied to this audio device. To make further changes, you can use the Properties dialog or run this wizard again.	
	Einish	cel

Please click on Finish to return to the Sound-Menu.



3	Lautsprecher High Definition Audio-Gerät Not plugged in	
	Digitales Ausgabegerät (SPDIF) High Definition Audio-Gerät Working	
0	Lautsprecher USB Audio Working	
	SPDIF-Schnittstelle USB Audio Working	

Now click Properties.

Seneral	Levels	Enhancements	Advanced	
Select config playba	the enhi uration. ack.	ancements to app Changes may not	oly <mark>for</mark> your currer t take effect until	n <mark>t speaker</mark> the next time you start
Dis Dis	able all e	enhancements		
E	lass Man	agement *		
	peaker F	1		
	oudness	Foulization		
	oddricoo	Equilization		
Enhar	ncement	Properties		
	Descript	ion: Speaker Fill o playback of s speaker syst	reates a virtual e stereo audio sour ems.	nvironment for ces on surround
	Provi	der: Microsoft		
	Sta	tus: Disabled		Settings
Rest	ore Defa	ults		▶ Preview ►

To hear stereo audio signals from all speakers, you have to checkmark the option Speaker Fill and click Apply. Finally you can close all windows. Your Aureon is now configured.

* This option will only appear if the full-range-speakers are not selected. If you do not hear the Bass please checkmark this option too.